


**DESCRIPTION:**

The JST06A-600B triac is suitable for general purpose AC switching. It can be used as an ON/OFF function in applications such as heating regulation, induction motor starting circuits, for phase control operation in light dimmers, motor speed controllers. By using an internal ceramic pad, JST06A-600B provides a rated insulation voltage of 2500 VRMS, complying with UL standards (File ref: E252906). Package TO-220A is RoHS compliant.

**MAIN FEATURES**

Symbol	Value	Unit
$I_{T(RMS)}$	6	A
$V_{DRM}/V_{RRM}$	600	V
$I_{GT\text{ I/II/III/IV}}$	50/50/50/70	mA

**ABSOLUTE MAXIMUM RATINGS**

Parameter	Symbol	Value	Unit
Storage junction temperature range	$T_{stg}$	-40-150	°C
Operating junction temperature range	$T_j$	-40-125	°C
Repetitive peak off-state voltage ( $T_j=25^\circ\text{C}$ )	$V_{DRM}$	600	V
Repetitive peak reverse voltage ( $T_j=25^\circ\text{C}$ )	$V_{RRM}$	600	V
RMS on-state current ( $T_c \leq 100^\circ\text{C}$ )	$I_{T(RMS)}$	6	A
Non repetitive surge peak on-state current (full cycle , $t_p=20\text{ms}$ , $T_j=25^\circ\text{C}$ )	$I_{TSM}$	65	A
Non repetitive surge peak on-state current (full cycle , $t_p=16.6\text{ms}$ , $T_j=25^\circ\text{C}$ )		72	
$I^2t$ value for fusing ( $t_p=10\text{ms}$ , $T_j=25^\circ\text{C}$ )	$I^2t$	21	$\text{A}^2\text{s}$
Critical rate of rise of on-state current ( $I_G=2 \times I_{GT}$ , $f=100\text{Hz}$ , $T_j=125^\circ\text{C}$ )	I - II III-IV	$dI/dt$	$\text{A}/\mu\text{s}$
Peak gate current ( $t_p=20\mu\text{s}$ , $T_j=125^\circ\text{C}$ )	$I_{GM}$	4	A
Average gate power dissipation ( $T_j=125^\circ\text{C}$ )	$P_{G(AV)}$	0.5	W
Peak gate power	$P_{GM}$	10	W

Peak pulse voltage (T <sub>j</sub> =25°C; non-repetitive,off-state;FIG.7)	V <sub>PP</sub>	4	kV
--	-----------------	---	----

**ELECTRICAL CHARACTERISTICS (T<sub>j</sub>=25°C unless otherwise specified)**

Symbol	Test Condition	Quadrant	Value		Unit
I <sub>GT</sub>	V <sub>D</sub> =12V R <sub>L</sub> =33Ω	I - II - III	MAX.	50	mA
		IV		70	
V <sub>GT</sub>		ALL	MAX.	1	V
V <sub>GD</sub>	V <sub>D</sub> =V <sub>DRM</sub> T <sub>j</sub> =125°C R <sub>L</sub> =3.3KΩ	ALL	MIN.	0.2	V
I <sub>L</sub>	I <sub>G</sub> =1.2I <sub>GT</sub>	I - III - IV	MAX.	70	mA
		II		80	
I <sub>H</sub>	I <sub>T</sub> =200mA		MAX.	60	mA
dV/dt	V <sub>D</sub> =400V Gate Open T <sub>j</sub> =125°C		MIN.	600	V/μs
(dV/dt)c	(dI/dt)c=2.7A/ms, T <sub>j</sub> =125°C		MIN.	10	V/μs
t <sub>on</sub>	I <sub>G</sub> =80mA I <sub>A</sub> =400mA I <sub>R</sub> =40mA T <sub>j</sub> =25°C	TYP.	3	μs	
t <sub>off</sub>			30		

**STATIC CHARACTERISTICS**


Symbol	Parameter		Value(MAX.)	Unit
V <sub>TM</sub>	I <sub>TM</sub> =8.5A t <sub>p</sub> =380μs	T <sub>j</sub> =25°C	1.5	V
V <sub>TO</sub>	Threshold voltage	T <sub>j</sub> =125°C	0.82	V
R <sub>D</sub>	Dynamic resistance	T <sub>j</sub> =125°C	57	mΩ
I <sub>DRM</sub>	V <sub>D</sub> =V <sub>DRM</sub> V <sub>R</sub> =V <sub>RRM</sub>	T <sub>j</sub> =25°C	5	μA
I <sub>RRM</sub>		T <sub>j</sub> =125°C	0.2	mA

**THERMAL RESISTANCES**


Symbol	Parameter	Value	Unit
R <sub>th(j-c)</sub>	junction to case (AC)	3	°C/W
R <sub>th(j-a)</sub>	junction to ambient (AC)	60	°C/W

**ORDERING INFORMATION**


<b>J</b>	<b>ST</b>	<b>06</b>	<b>A</b>	<b>-600</b>	<b>B</b>
JieJie Microelectronics Co., Ltd					
	Triacs				
		IT(RMS):6A			B:IGT1-3≤50mA IGT4≤70mA
			A:TO-220A(Ins)		600:V <sub>DRM</sub> / V <sub>RRM</sub> ≥600V

**MARKING**


**FIG.1** Maximum power dissipation versus RMS on-state current




**FIG.3:** Surge peak on-state current versus number of cycles




**FIG.5:** Non-repetitive surge peak on-state current for a sinusoidal pulse with width  $t_p < 20\text{ms}$ , and corresponding value of  $I^2t$  ( I - II :  $dI/dt < 100\text{A}/\mu\text{s}$ ; III-IV:  $dI/dt < 50\text{A}/\mu\text{s}$ )



**FIG.2:** RMS on-state current versus case temperature



**FIG.4:** On-state characteristics



**FIG.6:** Relative variations of gate trigger current, holding current and latching current versus junction temperature





FIG.7: Test circuit for inductive and resistive loads to IEC-61000-4-5 standards



## SHAPING AND SOLDERING PARAMETERS

Refer to 《Instructions for installation of plastic-sealed in-line power devices》 released by JieJie.


**ORDERING INFORMATION**

Order code	Voltage $V_{DRM}/V_{RRM}$ (V)	IGT(mA)		Package	Base qty. (pcs)	Delivery mode
		I -II -III	IV			
<b>JST06A-600B</b>	<b>600</b>	<b>50</b>	<b>70</b>	<b>TO-220A(Ins)</b>	<b>50</b>	<b>Tube</b>

**Document Revision History**


Date	Revision	Changes
Apr.14, 2023	A.1.0	Last updated

## PACKAGE MECHANICAL DATA



Ref.	Dimensions					
	Millimeters			Inches		
	Min.	Typ.	Max.	Min.	Typ.	Max.
A	4.40		4.60	0.173		0.181
B	0.61		0.88	0.024		0.035
C	0.46		0.70	0.018		0.028
C2	1.21		1.32	0.048		0.052
C3	2.40		2.72	0.094		0.107
D	8.60		9.70	0.339		0.382
E	9.80		10.4	0.386		0.409
F	6.25		6.85	0.246		0.270
G	2.40		2.70	0.094		0.106
H	28.0		29.8	1.102		1.173
L1	3.45		4.05	0.136		0.159
L2	1.14		1.70	0.045		0.067
L3	2.65		2.95	0.104		0.116
V1		45°			45°	

## DELIVERY MODE



PACKAGE	OUTLINE	TUBE (PCS)	INNER BOX (PCS)	PER CARTON
TO-220A	TUBE	50	1,000	5,000

Information furnished in this document is believed to be accurate and reliable. However, Jiangsu JieJie Microelectronics Co., Ltd. assumes no responsibility for the consequences of use without consideration for such information nor use beyond it. Information mentioned in this document is subject to change without notice, apart from that when an agreement is signed, Jiangsu JieJie complies with the agreement.

Products and information provided in this document have no infringement of patents. Jiangsu JieJie assumes no responsibility for any infringement of other rights of third parties which may result from the use of such products and information. This document supersedes and replaces all information previously supplied.

 is a registered trademark of Jiangsu JieJie Microelectronics Co., Ltd.

Copyright ©2023 Jiangsu JieJie Microelectronics Co., Ltd. Printed All rights reserved.